

## **53. HOW TO SETUP GROUPS (JUNE 2025)**


### **STEP 1**

Go to Device Access.




### **STEP 2**

Go To Device Group.



## STEP 3

Press Add.



## STEP 4

Enter the Group Title.



## STEP 5

Press Enter.




## STEP 6

Press OK.




## STEP 7

Select the Group.




## STEP 8

Click Import.




## STEP 9

Tick the cameras you want to add to the group.



## STEP 10


Press OK.






## STEP 11

The cameras will be added to the new group.




## STEP 12

All other cameras will remain in the default group.




## STEP 13

To add another group, press Add.



## STEP 14

Enter the Group Title.




## STEP 15

Press Enter.




## STEP 16

Press OK.




## STEP 17

Click on the new group.




## STEP 18

Press import.




## STEP 19

Choose the cameras to import into the group.




## STEP 20

Press OK.




## STEP 21

The cameras will be added to the new group.



## STEP 22

All other cameras will remain in the default group.






## STEP 23

To delete a group, click on the required group.




## STEP 24

Click delete.



## STEP 25


Press OK.



## STEP 26


The group will be deleted.

All cameras in the deleted group will return to the default group.




## STEP 27

To delete a single camera from a group, select the required group.




## STEP 28

Tick the required camera.



## STEP 29


Press Remove.



## STEP 30

Press OK.


The camera will return to the default group.



## STEP 31

To rename a group, select the required group.


Click Edit.



## STEP 32


Rename the Group.

Press Enter.



## STEP 33


Press OK.





## STEP 34

Once completed, close Device Access.




## STEP 35

Return to the desktop.



## STEP 36

Go to Live View.



## STEP 37

The cameras will now be arranged as per the configured groups.

